


SPECIAL TYPE



- 1 Name & Model No.----- TIMER GTN - F1 / F2 / M3 / M4
- 2 Time multiple / range setting switch -- dip switch
- 3 Count up lamp ----- LED (light up in red)
- 4 Time scale ----- 00-99
- 5 Source lamp ----- LED (light up in green)  
\* LED flickers brightly and dimly during the counting and light up steadily after counting up.
- 6 Adjusting switch ----- digital push-switch  
(+) increase, (-) decrease
- 7 External T.B ----- M3.5 screw
- 8 Protection cover ----- PC (clear)

GTN-F1/F2/M3/M4

RATING VOLTAGE	
* AC / DC 24V	
* AC 100~240V 50/60Hz	
* DC 120V	
TIME RANGE	
* 0.1~99sec.	
* 0.1~99min.	
* 0.1~990hrs.	

\* TIME SETTING VALUE : MULTIPLE x RANGE x SCALE

[T : Setting time, Rt : Reset time - above 0.5sec.]

APPLICATION	CONNECTION DIAGRAM	TIMING FLOWCHART
<p>GTN-F1 (2c) SIGNAL OFF DELAY</p>		
<p>GTN-F2 (2c) SIGNAL OFF DELAY</p>		
<p>GTN-M3 (1a, 2c) POWER ON DELAY</p>		
<p>GTN-M4 (1a, 2c) POWER ON INTERVAL</p>		